

# LED Security Lights With PIR Sensor



## Sensor Functions!

1. Always On: Set function lever to on-time. Lights always on; and can be controlled with a wall switch.
2. On with Motion Only: Set function lever to Auto. Lights turn on with motion detected from dusk to dawn with time dial)
3. On at 20% brightness from dusk to dawn with no motion detected: Set function lever to Dim. Lights turn on to full brightness when motion detected from dusk to dawn with time dial)







## Features

- Mounts flush on wall or 4" round weatherproof box
- Die-cast aluminum with powder coat finish
- High-impact polycarbonate lens
- CRI: 80
- Operating Temp: -40° F to 104° F
- Power factor: .90~.97
- Sensor angle: 180°
- Voltage: 120VAC 50/60Hz
- Suitable for Wet Locations, IP65
- 5-year warranty



## LED Security Lights With PIR Sensor, 120VAC, 180° Sensor, 100° Beam Angle (120° 28W) 80% Dim (Or Off) When No Motion Detected

Quick Search Code: S19990

	Product No	Description	Equivalency
	SLB-112-50K-P	28W 3400LM 5000K BRONZE	150 MH
	SLB-112-30K-P	28W 3400LM 3000K BRONZE	150 MH
	SLW-112-50K-P	28W 3400LM 3000K WHITE	150 MH
	SLW-112-30K-P	28W 3400LM 5000K WHITE	150 MH
	SLB-212-50K-P	20W 1900LM 5000K BRONZE	70 MH
	SLB-212-30K-P	20W 1900LM 3000K BRONZE	70 MH
	SLW-212-50K-P	20W 1900LM 5000K WHITE	70 MH
	SLW-212-30K-P	20W 1900LM 3000K WHITE	70 MH
	SLB-312-50K-P	30W 2800LM 5000K BRONZE	100 MH
	SLB-312-30K-P	30W 2800LM 3000K BRONZE	100 MH
	SLW-312-50K-P	30W 2800LM 5000K WHITE	100 MH
	SLW-312-30K-P	30W 2800LM 3000K WHITE	100 MH

Application

